

Shape Invariant Potentials for Effective Mass Schrödinger Equation

K A Samani* and F Loran†

*Department of Physics, Isfahan University of Technology (IUT),
Isfahan 84154, Iran*

Abstract

Using the method of shape invariant potentials, a number of exact solutions of one dimensional effective mass Schrödinger equation are obtained. The solutions with equi-spaced spectrum are discussed in detail.

1 Introduction

Since the introduction of the factorization method by Schrödinger [1] to solve the hydrogen atom problem algebraically, there has been a considerable effort to generalize this method and to find exactly (analytically) solvable potentials for the Schrödinger equation. One of the pioneering works in this line was done by Infeld and Hull [2]. They obtained a wide class of exactly solvable potentials using the factorization method. After the introduction of supersymmetric quantum mechanics [3], the concept of a shape invariant potential (SIP) was introduced by Gendenshtein [4] in 1983. The Schrödinger equation with a SIP has exact solution and its energy eigenvalues can be obtained algebraically. The method of shape invariant potentials is also applied to some other equations like Fokker - Plank equation as well [6]. Although SIPs are widely studied and many families of them are obtained [5], but the problem of the classification of SIPs has not been completely solved yet.

In this paper we apply the method of SIPs to effective mass Schrödinger equation and obtain its exact solutions in a specific ansatz. Effective mass Schrödinger equation was introduced by BenDaniel and Duke [7] in 1966 to explain the behavior of electrons in the junctions of semiconductors. It also have some applications in heterostructures, graded alloys, and quantum wells [8], [9], [10].

Recently, effective mass Schrödinger equation is studied by some authors and some of its exact solutions are obtained [11], [12], [13]. Here we show that the method of shape invariant potentials applied to this problem leads to a wide class of exact solutions.

*E-mail address: samani@cc.iut.ac.ir

†E-mail address: loran@cc.iut.ac.ir

The paper is organized as follows. In section 2 we review the method of SIPs and its generalized form for effective mass Schrödinger equation. In sections 3 and 4 we study two main classes of generalized shape invariant potentials(GSIPs) corresponding to special choices for the parameter dependence of the potential. Such parameter dependence have been considered to obtain SIPs for ordinary Schrödinger equation in reference [5] and references therein. Due to the importance of quantum systems with equi-spaced energy levels, we investigate them separately in each case. Section 5 is devoted to summary and concluding remarks.

2 Generalized Shape Invariant Potentials (GSIPs)

In this section we review the method of SIPs for effective mass Schrödinger equation. Consider an eigenvalue problem given by

$$H\psi_n(x) = E_n\psi_n(x) , \quad (1)$$

where H is given by

$$H = -\frac{d}{dx} \frac{1}{2m(x)} \frac{d}{dx} + V(x) . \quad (2)$$

Here $m(x)$ is the position depended effective mass and $V(x)$ is the potential.

Suppose that the minimum eigenvalue of H is E_0 . Let us define a new Hamiltonian $H_1 := H - E_0$. The Hamiltonian H_1 can be written in the following form

$$H_1 = -\frac{d}{dx} \frac{1}{2m(x)} \frac{d}{dx} + V_1(x) , \quad (3)$$

in which $V_1(x) = V(x) - E_0$. The ground state energy of H_1 is zero, i. e. the spectrum of H_1 is non negative. Consequently the Hamiltonian H_1 can be assumed to be

$$H_1 = A^\dagger A , \quad (4)$$

where A is a first order differential operator of the form

$$A = U(x) \frac{d}{dx} + W(x) . \quad (5)$$

Inserting A from Eq. (5) in Eq. (4) and comparing the result with Eq. (3) one gets

$$\frac{1}{2m(x)} = U^2(x) , \quad (6)$$

$$V_1(x) = W^2(x) - [U(x)W(x)]' . \quad (7)$$

Here, a $'$ indicates the derivative with respect to x . Eq. (7) is a generalization of the well known Riccati equation. We call the solution of this equation [5], $W(x)$, the *superpotential*.

Next we define the Hamiltonian H_2 as follows

$$H_2 := AA^\dagger \equiv -\frac{d}{dx} \frac{1}{2m(x)} \frac{d}{dx} + V_2(x) . \quad (8)$$

Then the potential $V_2(x)$ reads

$$\begin{aligned} V_2(x) &= W^2(x) + [U(x)W(x)]' - 2U'(x)W(x) - U(x)U''(x) , \\ &W^2(x) - [U(x)W(x)]' + 2U(x)W'(x) - U(x)U''(x) . \end{aligned} \quad (9)$$

The Hamiltonian H_2 is called the supersymmetric partner of H_1 [5]. It can be easily shown that H_1 and H_2 has the same spectrum except for the ground state of H_1 . Suppose that $\psi_1(x)$ is an eigenfunction of H_1 with eigenvalue E_1 . Then in view of Eq. (4) we have

$$A^\dagger A \psi_1(x) = E_1 \psi_1(x) . \quad (10)$$

Using Eq. (8) it is easily seen that $A \psi_1(x)$ is an eigenfunction of H_2 with eigenvalue E_1 , provided that $\psi_1(x)$ is not the ground state wave function.

One can repeat the above procedure for H_2 and get the supersymmetric partner of H_2 . Then one arrives at a hierarchy of Hamiltonians which their spectrum are essentially the same. Now suppose that the potentials $V_1(x)$ and $V_2(x)$ depend on some parameters which we show them in a compact form by a . The shape invariance condition is

$$V_2(x, a_1) = V_1(x, a_2) + R(a_1) , \quad (11)$$

where $a_2 = F(a_1)$ is a function of a_1 and $R(a_1)$ is independent of x . If these conditions are fulfilled, the spectrum of H_1 can be found algebraically [5]:

$$E_n = \sum_{i=1}^n R(a_i) . \quad (12)$$

In what follows, we use this method to find the exact solutions of effective mass Schrödinger equation considering the super potentials in the ansatz:

$$W(x, a) = ag(x) + f(x) + \frac{1}{a}h(x) . \quad (13)$$

Inserting $W(x, a)$ from Eq. (13) in Eqs. (7) and (9), the shape invariance condition (11) gives

$$\begin{aligned} & (a_2^2 - a_1^2)g^2(x) + \left(\frac{1}{a_2^2} - \frac{1}{a_1^2}\right)h^2(x) + 2(a_2 - a_1)g(x)f(x) + 2\left(\frac{1}{a_2} - \frac{1}{a_1}\right)h(x)f(x) \\ & - \left[U(x)(a_2 - a_1)g(x) + U(x)\left(\frac{1}{a_2} - \frac{1}{a_1}\right)h(x)\right]' - 2U(x)\left[a_1g(x) + \frac{1}{a_1}h(x) + f(x)\right]' \\ & + U(x)U''(x) + R(a_1) = 0 . \end{aligned} \quad (14)$$

Before starting to study Eq. (14), we make a definition for the future convenience:

$$Y(x) := \int^x \frac{dx'}{U(x')} . \quad (15)$$

There is also a comment in order on the square integrability of the wave functions. According to Eq. (4) the ground state of H_1 is given by $A\psi_0(x) = 0$. This, together with definition (5) leads to

$$\psi_0(x) \sim \exp \left[- \int^x \frac{W(x')}{U(x')} dx' \right] . \quad (16)$$

Then the square integrability of $\psi_0(x)$ leads to

$$\int_{-\infty}^{\infty} \psi_0^2(x) dx = \int_{-\infty}^{\infty} \exp \left[-2 \int^x \frac{W(x')}{U(x')} dx' \right] < \infty . \quad (17)$$

This condition puts some restrictions on acceptable $W(x)$ and $U(x)$. In fact the following condition must be fulfilled

$$\lim_{x \rightarrow \pm\infty} \int^x \frac{W(x')}{U(x')} dx' = +\infty. \quad (18)$$

If $\frac{W(x)}{U(x)}$ has definite signs for $x \rightarrow \pm\infty$, then there is a simple condition which guarantees Eq. (18) [14]. Let us define

$$\left(\frac{W}{U}\right)_{\pm} := \lim_{x \rightarrow \pm\infty} \frac{W(x)}{U(x)}. \quad (19)$$

Then, to fulfill Eq. (18), it is sufficient that

$$\text{sign}\left(\frac{W}{U}\right)_{+} = -\text{sign}\left(\frac{W}{U}\right)_{-}. \quad (20)$$

It can be shown that this condition also ensures the square integrability of excited states wave functions [5].

3 GSIPs of type $W(x, a) = f(x) + a$

In this section we consider GSIPs whose superpotentials are of the form

$$W(x, a) = f(x) + a. \quad (21)$$

This means that in Eq. (13) we have put $g(x) = 1$ and $h(x) = 0$. Then the shape invariance condition gives

$$U(x) [U'(x) - 2f(x)]' - (a_2 - a_1) [U'(x) - 2f(x)] + (a_2^2 - a_1^2) + R(a_1) = 0. \quad (22)$$

In this equation $U(x)$ and $f(x)$ are independent of parameter a_1 . Therefore there are only two ways for Eq. (22) to be consistent. The first way is that $U'(x) - 2f(x) = \text{const.} =: 2u_0$. Then the superpotential is given by $W(x, a) = \frac{1}{2}U'(x) + a - u_0$. and Eq. (22) implies that $R(a_1) = (a_1^2 - a_2^2) - 2u_0(a_1 - a_2)$. Absorbing u_0 in a , one gets $R(a_1) = (a_1^2 - a_2^2)$. Therefore in this case a_2 is an arbitrary function of a_1 provided $R(a_1) = a_1^2 - a_2^2 > 0$ to ensure that the energy eigenvalues are non negative.

The second way is that $a_1 - a_2$ and $(a_2^2 - a_1^2) + R(a_1)$ be independent of parameter, i. e.

$$R(a_1) = \alpha(2a_1 - \alpha) + R_0, \quad (23)$$

$$a_2 = a_1 - \alpha, \quad (24)$$

where α and R_0 are some real constants. Using these conditions and defining $u(x) := U'(x) - 2f(x)$ we can write Eq. (22) in the following form

$$U(x)u'(x) + \alpha u(x) + R_0 = 0. \quad (25)$$

Before trying to solve this equation let us have a look at the spectrum of H_1 . The energy eigenvalues of H_1 are given by

$$E_n = \sum_{i=1}^n R(a_i) = n(R_0 + 2a_1\alpha - n\alpha^2). \quad (26)$$

This equation shows that for $\alpha = 0$ the energy levels are equi-spaced. Due to the importance of systems with equi-spaced energy levels we consider two distinct cases corresponding to $\alpha = 0$ and $\alpha \neq 0$ separately. We call solutions with equi-spaced energy levels *oscillator like solutions*.

3.1 Oscillator like Solutions

For $\alpha = 0$ Eq. (25) gives

$$u(x) = -R_0 Y(x) , \quad (27)$$

where $Y(x)$ is defined by Eq. (15). Therefore the superpotential is

$$W(x, a) = \frac{1}{2} [U'(x) + R_0 Y(x)] + a , \quad (28)$$

and the potential $V_1(x, a_1)$ is given by

$$V_1(x, a) = \frac{1}{4} [(R_0 Y(x) + 2a)^2 - 2R_0] + V_0(x) , \quad (29)$$

in which

$$V_0(x) := -\frac{1}{4}U'^2(x) - \frac{1}{2}U(x)U''(x) . \quad (30)$$

The energy eigenvalues are $E_n = nR_0$, $n = 0, 1, 2, \dots$. Since the energy eigenvalues are non negative we should have $R_0 > 0$. because the energy eigenvalues are non negative.

Now we can obtain the zero energy eigenstate using Eq. (16)

$$\psi_0(x) \sim |U(x)|^{-1/2} \exp \left(-\frac{R_0}{4} Y^2(x) - aY(x) \right) . \quad (31)$$

It can be easily verified that the ground state wave function is normalizable i. e. Eq. (17) is fulfilled. The results of this subsection is summarized in table 1.

3.1.1 Examples

Example 1: If $U(x) = \frac{1}{\sqrt{2m}} = \text{const}$, the system is a harmonic oscillator; the most simple system with equi-spaced energy levels.

Example 2: For $U(x) = \frac{1}{2x}$ we have $Y(x) = x^2$. The effective mass and potential are given by

$$m(x) = 2x^2 , \quad (32)$$

$$V_1(x, a) = \left(\frac{R_0}{2} x^2 + a \right)^2 - \frac{5}{16x^4} - \frac{R_0}{2} . \quad (33)$$

Example 3: For $U(x) = \frac{1}{\cosh x}$ we have $Y(x) = \sinh x$ and $m(x) = \frac{1}{2} \cosh^2 x$. This form of position dependent mass is considered by some authors in graded alloys [10]. The potential is given by

$$V_1(x, a) = \frac{1}{4} \left[(R_0 \sinh x + 2a)^2 + \frac{\sinh^2 x - 2}{\cosh^4 x} - 2R_0 \right] . \quad (34)$$

3.2 Exponential Solutions

If $\alpha \neq 0$, by redefinition of the function $f(x)$ and the parameter a we can put $R_0 = 0$. The redefinition is given by the following equations

$$a \rightarrow \tilde{a} = a + \frac{R_0}{2\alpha} , \quad (35)$$

$$f(x) \rightarrow \tilde{f}(x) = f(x) - \frac{R_0}{2\alpha} . \quad (36)$$

Under this redefinition, $W(x, a)$ does not change but $R(a_1)$ changes as

$$R(a_1) \rightarrow \tilde{R}(\tilde{a}_1) = \alpha(2\tilde{a}_1 - \alpha) , \quad (37)$$

and Eq. (25) can be rewritten as

$$U(x)\tilde{u}'(x) + \alpha\tilde{u}(x) = 0 . \quad (38)$$

We conclude that for $\alpha \neq 0$ one can always put $R_0 = 0$. The solution of Eq. (38) is

$$\tilde{u}(x) = u_0 \exp(-\alpha Y(x)) . \quad (39)$$

We call these solutions, *exponential solutions*. The superpotential $W(x, a)$ is therefore

$$W(x, a) = \frac{1}{2} [U'(x) - u_0 \exp(-\alpha Y(x))] + a , \quad (40)$$

and the potential is given by

$$V_1(x, a) = \frac{1}{4} [(u_0 e^{-\alpha Y(x)} - 2a)^2 - 2\alpha u_0 e^{-\alpha Y(x)}] + V_0(x) , \quad (41)$$

in which $V_0(x)$ is defined in Eq. (30). The energy eigenvalues are

$$E_n = \alpha n(2a_1 - \alpha n) . \quad (42)$$

The ground state which is given by Eq. (16) takes the following form

$$\psi_0(x) \sim |U(x)|^{-1/2} \exp\left(\frac{-u(x)}{2\alpha} - a_1 Y(x)\right) . \quad (43)$$

The above results are summarized in the table 2.

Examples

Example 1: $U(x) = U_0 = \text{const.}$ With this choice for $U(x)$ we arrive at the Morse potential for ordinary Schrödinger equation which is a well known SIP [5].

Example 2: $U(x) = -\frac{\alpha}{2}x$. In this case, choosing $u_0 = 1$ in Eq. (39), one gets

$$W(x, a) = -\frac{1}{4} (\alpha + 2x^2) + a , \quad (44)$$

$$V_1(x, a) = \frac{1}{4}x^4 - (\alpha/2 + a)x^2 - \frac{\alpha^2}{16} + a^2 , \quad (45)$$

$$\psi_0(x) \sim |x|^{\frac{2a_1}{\alpha} - \frac{1}{2}} \exp\left(-\frac{x^2}{2\alpha}\right) . \quad (46)$$

4 GSIPs of Type $W(x, a) = ag(x) + f(x)$

This ansatz is obtained putting $h(x) = 0$ in Eq. (13). Applying the shape invariance condition we arrive at

$$\begin{aligned} & (a_2^2 - a_1^2)g^2(x) + (a_2 - a_1)g(x) [2f(x) - U'(x)] \\ & - (a_1 + a_2)U(x)g'(x) - U(x) [2f(x) - U'(x)]' + R(a_1) = 0. \end{aligned} \quad (47)$$

Assuming that $a_1 - a_2 = \alpha$, one gets

$$\begin{aligned} & \alpha^2 g^2(x) - 2\alpha f(x)g(x) + \alpha [U(x)g(x)]' - 2U(x)f'(x) + U(x)U''(x) \\ & - 2a_1 (\alpha g^2(x) + U(x)g'(x)) + R(a_1) = 0. \end{aligned} \quad (48)$$

Since $U(x)$, $f(x)$, $g(x)$, and α are parameter independent, we conclude from the above equation that

$$\alpha^2 g^2(x) - 2\alpha f(x)g(x) + \alpha [U(x)g(x)]' - 2U(x)f'(x) + U(x)U''(x) + C_1 = 0, \quad (49)$$

$$-2a_1 (\alpha g^2(x) + U(x)g'(x)) + R(a_1) - C_1 = 0. \quad (50)$$

In the same way Eq. (50) implies that

$$\alpha g^2(x) + U(x)g'(x) + C_2 = 0, \quad (51)$$

$$R(a_1) = C_1 - 2a_1 C_2. \quad (52)$$

Therefore energy eigenvalues are

$$E_n = n^2 \alpha C_2 + n[C_1 - (2a_1 + \alpha)C_2]. \quad (53)$$

Using Eq. (51) in Eq. (49) one finds

$$\alpha g(x)u(x) + U(x)u'(x) + C_1 - \alpha C_2 = 0, \quad (54)$$

where $u(x) = U'(x) - 2f(x)$. Eq. (53) indicates that for $\alpha C_2 = 0$ the energy eigenvalues are equi-spaced. In the following we discuss three different families of solutions corresponding to $\alpha C_2 = 0$, $\alpha C_2 > 0$, and $\alpha C_2 < 0$.

4.1 Oscillator like solutions ($\alpha C_2 = 0$)

These are solutions with equi-spaced spectrum (see Eq. (53)). Three different cases can be realized as follows,

Case 1: $\alpha = C_2 = 0$. In this case according to Eq. (51), $g(x)$ should be a constant function of x . We have discussed this case in section 3.

Case 2: $\alpha = 0$ and $C_2 \neq 0$. In this case Eqs. (51) and (54) are easily solved and we get $g(x) = -C_2 Y(x)$ and $u(x) = -C_1 Y(x)$. Therefore,

$$W(x, a) = \frac{1}{2}U'(x) + \frac{1}{2}(C_1 - 2aC_2)Y(x), \quad (55)$$

$$E_n = n((C_1 - 2a_1 C_2)). \quad (56)$$

One can redefine the parameter a as $a \rightarrow \tilde{a} = \frac{C_1}{2} - aC_2$. The results are summarized in the table 3.

Case 3: $\alpha \neq 0$ and $C_2 = 0$. In this case from Eq. (51) one finds

$$g(x) = \frac{1}{\alpha Y(x)} . \quad (57)$$

Then substituting this solution in Eq. (54) we have

$$u(x) = -\frac{C_1}{2}Y(x) - \frac{C_3}{Y(x)} , \quad (58)$$

where C_3 is a constant. In fact C_3 is not so important and can be absorbed in the parameter a . See table 4

4.2 Trigonometric Solutions ($\alpha C_2 > 0$)

Putting $k := \sqrt{C_2\alpha}$ it is straightforward to solve Eqs. (51) and (54) to get

$$g(x) = -\frac{k}{\alpha} \tan[kY(x)] , \quad (59)$$

and

$$u(x) = -\frac{C_1 - \alpha C_2}{k} \tan[kY(x)] - C_3 \sec[kY(x)] . \quad (60)$$

Then the superpotential is obtained:

$$W(x, a) = \left(-\frac{ka}{\alpha} + \frac{C_1 - k^2}{2k}\right) \tan(kY) + \frac{C_3}{2} \sec(kY) . \quad (61)$$

Redefining the parameter a as

$$a \rightarrow \tilde{a} = -\frac{ka}{\alpha} + \frac{C_1 - k^2}{2k} , \quad (62)$$

we have $\tilde{a} := \tilde{a}_1 - \tilde{a}_2 = -k$. Using this redefinition one can write the general form of superpotential as

$$W(x, a) = -a \tan(\alpha Y) + b \sec(\alpha Y) + \frac{1}{2}U'(x) , \quad (63)$$

where $b = -\frac{C_3}{2}$. The energy eigenvalues are given by

$$E_n = n\alpha(n\alpha - 2a_1) . \quad (64)$$

Finally the ground state is given by

$$\psi_0(x) \sim |U(x)|^{\frac{-1}{2}} |\sec(\alpha Y)|^{\frac{a}{\alpha}} |\tan(\alpha Y) + \sec(\alpha Y)|^{-\frac{b}{\alpha}} . \quad (65)$$

It is remarkable that for $U(x) = \text{const.}$ the above solution reduces to the Scarf I potential which is a SIP for ordinary Schrödinger equation [5]. The results of this subsection is summarized in table 5

4.3 Hyperbolic Solutions ($\alpha C_2 < 0$)

Considering the definition $k := \sqrt{-C_2\alpha}$ one can solve Eqs. (51) and (54) to get

$$g(x) = \frac{k}{\alpha} \tanh[kY(x)] , \quad (66)$$

and

$$u(x) = -\frac{C_1 - \alpha C_2}{k} \tanh[kY(x)] - C_3 \operatorname{sech}[kY(x)] . \quad (67)$$

Then the superpotential can be found as

$$W(x, a) = \left(\frac{ka}{\alpha} + \frac{C_1 + k^2}{2k}\right) \tanh(kY) + \frac{C_3}{2} \operatorname{sech}(kY) . \quad (68)$$

Now we redefine the parameter a as

$$a \rightarrow \tilde{a} = \frac{ka}{\alpha} + \frac{C_1 + k^2}{2k} . \quad (69)$$

After this redefinition of a we have $\tilde{\alpha} := \tilde{a}_1 - \tilde{a}_2 = k$. Therefore the general form of superpotential can be given as

$$W(x, a) = a \tanh(\alpha Y) + b \operatorname{sech}(\alpha Y) + \frac{1}{2} U'(x) , \quad (70)$$

where $b = \frac{C_3}{2}$. The energy eigenvalues are given by

$$E_n = n\alpha(n\alpha - 2a_1) , \quad (71)$$

and the ground state is

$$\psi_0(x) \sim |U(x)|^{\frac{-1}{2}} |\operatorname{sech}(\alpha Y)|^{\frac{-a}{\alpha}} |\tanh(\alpha Y) + \operatorname{sech}(\alpha Y)|^{-\frac{b}{\alpha}} . \quad (72)$$

For $U(x) = \text{const.}$ the above solution reduces to the Scarf II potential which is a SIP for ordinary Schrödinger equation [5]. The results of this subsection are summarized in table 6

5 Concluding Remarks

In this paper we studied exact solutions of effective mass Schrödinger equation using the method of shape invariant potentials. We considered an ansatz in which the superpotential takes the form

$$W(x, a) = ag(x) + f(x) + \frac{h(x)}{a} . \quad (73)$$

Assuming $h(x)$ be vanishing, the exact solutions for the Schrödinger equation are studied and a wide class of solutions with equi-spaced spectrum are obtained. Following the general arguments of the paper, it can be verified that if $h(x)$ is non-vanishing then it should be simply a constant. In this case the shape invariance condition requires $m(x)$ to be constant. Thus if $h(x) \neq 0$, one obtains the SIPs for the ordinary Schrödinger equation. The main results of the this study are summarized in tables 1 – 6.

Acknowledgment

Financial supports from Isfahan University of Technology (IUT) is acknowledged.

References

- [1] E. Schrödinger, Proc. Roy. Irish Acad. **A46**, 9 (1940).
- [2] L. Infeld and T. E. Hull, Rev. Mod. Phys. **23**, 21 (1951).
- [3] E. Witten, Nucl. Phys. **B188**, 513 (1981).
- [4] L. Gendenshtein, JETP Lett. **38**, 356 (1983).
- [5] f. Cooper, A. Khare, and U. Sukhatme, Phys. Rep. **251**, 267 (1995).
- [6] M. Bernstein and L. S. Brown, Phys. Rev. Lett. **52**, 1933 (1984).
- [7] D. J. BenDaniel and C. B. Duke, Phys. Rev. **152**, 683 (1966).
- [8] G. Bastard, *Wave Mechanics Applied to Semiconductor Heterostructures*, Les Editions de Physique, Les ulis, France (1988).
- [9] D. Bessis and G. A. Mezincescu, Microelectronic J. **30**, 953 (1999).
- [10] V. Milanović and Z. Ikonić, Phys. Rev. **B54**, 1998 (1996).
- [11] B. Roy and P. Roy, J. Phys. A: Math. Gen. **35**, 3961 (2002).
- [12] Bülent Gönül, Okan Özer, Beşire Gönül, and Fatma Üzgün, Mod. Phys. Lett. **A17**, 2453 (2002).
- [13] A. D. Alhaidari, Phys. Rev. **A66**, 042116 (2002).
- [14] L. E. Gendenshtein and I. V. Krive, Sov. Phys. Ups. **28**, 645 (1985).

Superpotential	$W(x, a) = \frac{1}{2} [U'(x) + R_0 Y(x)] + a$
Potential	$V_1(x, a) = \frac{1}{4} [(R_0 Y(x) + 2a)^2 - 2R_0] + V_0(x)$
Energy eigenvalues	$E_n = nR_0$
Ground state	$\psi_0(x) = N U(x) ^{-1/2} \exp \left(-\frac{R_0}{4} Y^2(x) - aY(x) \right)$

Table 1: GSIPs of type $W(x, a) = f(x) + a$; Oscillator like solutions

Superpotential	$W(x, a) = \frac{1}{2} [U'(x) - u_0 \exp(-\alpha Y(x))] + a$
Potential	$V_1(x, a) = \frac{1}{4} [(u_0 e^{-\alpha Y(x)} - 2a)^2 - 2\alpha u_0 e^{-\alpha Y(x)}] + V_0(x)$
Energy eigenvalues	$E_n = \alpha n(2a_1 - \alpha n)$
Ground state	$\psi_0(x) \sim U(x) ^{-1/2} e^{\frac{-u(x)}{2\alpha} u(x) - a_1 Y(x)}$

Table 2: GSIPs of type $W(x, a) = f(x) + a$; Exponential solutions

Superpotential	$W(x, a) = \frac{1}{2}U'(x) + aY(x)$
Potential	$V_1(x, a) = a^2Y^2(x) - a + V_0(x)$
Spectrum	$E_n = 2a_1n$
Ground state	$\psi_0(x) \sim U(x) ^{-1/2} \exp\left(\frac{-a}{2}Y^2(x)\right)$

Table 3: GSIPs of type $W(x, a) = ag(x) + f(x)$; Oscillator like solutions (I)

Superpotential	$W(x, a) = \frac{1}{2}U'(x) + \frac{C_1}{4}Y(x) + \frac{a}{\alpha Y(x)}$
Potential	$V_1(x, a) = \frac{C_1^2}{16}Y^2(x) + \left(\frac{a^2}{\alpha^2} + \frac{a}{\alpha}\right) \frac{1}{Y^2(x)} + \frac{C_1}{2} \left(\frac{a}{\alpha} - \frac{1}{2}\right) + V_0(x)$
Spectrum	$E_n = C_1n$
Ground state	$\psi_0(x) \sim U(x) ^{-1/2} Y(x) ^{-\frac{a}{\alpha}} \exp\left(-\frac{C_1}{8}Y^2(x)\right)$

Table 4: GSIPs of type $W(x, a) = ag(x) + f(x)$; Oscillator like solutions (II)

Superpotential	$W(x, a) = -a \tan(\alpha Y) + b \sec(\alpha Y) + \frac{1}{2}U'(x)$
Potential	$V_1(x, a) = (a \tan(\alpha Y) - b \sec(\alpha Y))^2$ $-\alpha \sec(\alpha Y)(b \tan(\alpha Y) - a \sec(\alpha Y)) + V_0(x)$
Spectrum	$E_n = n\alpha(n\alpha - 2a_1)$
Ground state	$\psi_0(x) \sim U(x) ^{\frac{-1}{2}} \sec(\alpha Y) ^{\frac{a}{\alpha}} \tan(\alpha Y) + \sec(\alpha Y) ^{-\frac{b}{\alpha}}$

Table 5: GSIPs of type $W(x, a) = ag(x) + f(x)$; Trigonometric solutions

Superpotential	$W(x, a) = a \tanh(\alpha Y) + b \operatorname{sech}(\alpha Y) + \frac{1}{2}U'(x)$
Potential	$V_1(x, a) = (a \tanh(\alpha Y) - b \operatorname{sech}(\alpha Y))^2$ $+\alpha \operatorname{sech}(\alpha Y)(b \tanh(\alpha Y) - a \operatorname{sech}(\alpha Y)) + V_0(x)$
Spectrum	$E_n = n\alpha(n\alpha - 2a_1)$
Ground state	$\psi_0(x) \sim U(x) ^{\frac{-1}{2}} \operatorname{sech}(\alpha Y) ^{-\frac{a}{\alpha}} \tanh(\alpha Y) + \operatorname{sech}(\alpha Y) ^{-\frac{b}{\alpha}}$

Table 6: GSIPs of type $W(x, a) = ag(x) + f(x)$; Hyperbolic solutions